

## PROMS

| PROM                       | Nascom Device | Type                      | Fujitsu | Signetics | AMD   | MMI  | National | TI     | Harris |
|----------------------------|---------------|---------------------------|---------|-----------|-------|------|----------|--------|--------|
| N2 I/O<br>N2V/2H<br>N2MD/3 | IM5600CPE     | 32*8<br>Open<br>Collector | 7111    | 82S23     | 27S18 | 6330 | 74S188   | 18SA30 | 7602   |
| N2DB/3H                    | IM5623CPE     | 256*4 Tri-<br>State       | 7114    | 82S129    | 27S21 | 6301 | 74S287   | 24S10  | 7611   |

# **PROM Contents**

## ***N2IO/1***

FF FF FF FF FF FF FF FF  
FD EF DF 7F FF FF FF FF  
FE FB F7 BF FF FF FF FF  
FF FF FF FF FF FF FF FF

## ***N2MD/3***

FE FD FB FB F7 F7 FF FF  
FF FF FF FF FF FF FF FF  
FF FF FF FF FF FF EF EF  
DF DF BF BF 7F 7F 7F 7F

## ***N2MD CP/M – Gemini?***

FE FD FF FF FF FF FF FF  
FF FF FF FF FF FF FF FF  
FF FF FF FF FF FF FF FF  
DF DF BF BF 7F EF FB F7

## ***N2MD CP/M Lucas***

FE FD FB FB FF FF FF FF  
FF FF FF FF FF FF FF FF  
FF FF FF FF FF FF FF FF  
F7 F7 EF EF DF DF BF F7